



F1842044 Anodized Champagne

Coordinates Suspension 1 CLIII


Designed by Michael Anastassiades, 2020


32W - 1920lm - 2700K - CRI> 95

Coordinates is a lighting system with diffuse light composed of horizontal and vertical luminaries arranged in a bright grid of various shapes and complexities. Each element is made of extruded anodized aluminium with a champagne finish and a diffuser in platinum optical silicone with an integrated LED strip (CRI 95). Each element is powered and supported by an invisible electrical and mechanical connection designed specifically to allow for the composition of the 4 hanging models (S1, S2, S3, S4) with 2.4-m cables. The 'S Module' is also available. Its geometry was designed to be repeated to create large grids for custom installations. Each Coordinates configuration includes its own ceiling rose, whose integrated electronics allow for the use of different dimmer systems: push, 1-10, DALI. In the absence of these systems, the amount of light can be set during installation with the push system included in the rose. The related CI III version is also available for each configuration for installations with a remote power supply.

Are you a professional and your project needs consulting and support?

BOOK AN APPOINTMENT





Main specifications

EAN	8059607032589		
Mounting	Suspension		
Environments	Indoor dry location		
Light Source Type	LED		
LED type	LED Module		
Power (W)	32		
System flux (lm)	1920		

Physical

Colour	Anodized Champagne
Length (mm)	780
Cord length (mm)	2400
Canopy dimension (mm)	29
Canopy width (mm)	61
Net weight (kg)	1.2
Package height (mm)	0
Package width (mm)	0
Package length (mm)	0
Package volume (m3)	0.02
IP internal	20

Ecodesign and Energy Labelling

This product contains a light source of energy efficiency class **F**



Replaceable (LED only) light source by a professional



















Photometric

Lighting type	Total
Light distribution	Asymmetric
CCT (K)	2700
CRI>	95

Electrical

Insulation class	III	
Main voltage (Vac)	48	
LED voltage Vf (Vdc)	null	
Driver	Remote excluded	
Dimming type	Electronic 48V	
Batteries inside	No	

Accessories & Power Supply





OPTIONAL

RF29208


48Vdc 80W Power supply

OPTIONAL

RF26994

12-48V Led Dimmer

Spare Parts



01.	Assembly Rose Cover for	RF1874144
	Coordinates S CLIII Anodized	
	Champagne	
02.	Rod Assembly L780 H-06 Agent	RF31373
03.	Rod Assembly L780 SH-03 Agent	RF31372
04.	Rod Assembly L780 SA-37	RF31437
	Anodized Champagne	









RF1874144

Assembly Rose Cover for Coordinates S CLIII Anodized Champagne



RF31373

Rod Assembly L780 H-06 Agent

RF31372

Rod Assembly L780 SH-03 Agent

RF31437

Rod Assembly L780 SA-37 Anodized Champagne